

BOM of PicoCOM2 carrierboard (PCOM-Startinterf2)

08.06.2009

Quantity	Articel	Type	Comment
1,00	B.CKV.2.S	22pF/50V / SMD, 0805	various
4,00	B.CKV.22	270pF/ 50V / 5% / SMD, 1206	various
10,00	B.CKV.3.S	100nF/50V / SMD, 1206	various
4,00	B.CKV.15.S	470nF/50V / SMD, 1206	various
4,00	B.CTA.4.S	4,7uF/10V / SMD, Typ: B	Sprague
7,00	B.CKV.26	10uF/10V / SMD, 1206	muRata
2,00	B.CTA.3.S	100uF/6,3V / SMD, Typ: D	various
2,00	B.EMVSUP.1	PGB102ST23WR	Littlefuse
1,00	B.DSI.3.S	SM4007 / MELF	Ersatztyp für SM4001, kein spez. Herst.
1,00	B.ICIF.32.S	TPS2080D / SMD, SO-08	Texas Instruments
1,00	B.ICIF.17.S	SP211CA-LF / SMD, SSOP-28	Sipex Corporation
1,00	B.ICLOG.26.S	74LCX245PW / SMD, TSSOP-20 (PW20)	SN74LVC245APWR
3,00	B.ICLOG.28.S	74AHC245PWR / SMD, TSSOP-20 (PW20)	74VHC245MTC/74VHC245TTR
1,00	B.ICIF.7.S	PCA82C250T / SMD, SO-8	Philips Semiconductor, CAN-Bus-Treiber
1,00	B.ICLOG.33	74LVC14 / SMD, SO-14 (DO14)	various
1,00	B.ICANA.40	NCP1529ASNT1G / TSOP-5	ON Semiconductor
1,00	B.ICANA.16.S	TLC7733ID / SMD, SO-8	Texas Instruments
1,00	B.L.15.S	TG110-S050N2RL	2fach Übertrager für Twisted Pair, HALO
1,00	B.L.20	3,3uH / 2A / WE-TPC Typ M	Würth Elektronik, Typ: 744042003
2,00	B.DLED.6.B	TLMY3100 / SMD	VLMY31K1L2-GS08
2,00	B.R000.1.S	0R00/0,25W / SMD,1206	various
3,00	B.R120.1.S	120R / 0,25W / 1% / SMD, 1206	various
1,00	B.R1K.2.S	1k/0,25W / SMD, 1206	various
1,00	B.R150K.1	150k/0,25W / SMD, 1206	various
1,00	B.R200K.2.S	200k/0,25W / SMD, 1206	various
1,00	B.R300K.1	300k / 0,25W / SMD, 1206	various
1,00	B.R.680K.2	680k/0,25W / SMD, 1206	various
3,00	B.RN4k7.1.S	4*4k7 / 0,063W / 1206	YAGEO/KOA CN1J 4 4,7k 5%
1,00	B.RN10k.2.S	4*10k / 0,063W / 1206	YAGEO/KOA CN1J 4 10k 5%
1,00	B.RN15k.1.S	4*15k / 0,063W / 1206	YAGEO/KOA CN1J 4 15k 5%
2,00	B.TNPN.4	PUMH7 / SMD, SOT-363	Philips
1,00	B.TPMFP.2.S	Si2301BDS / SOT-23 / P-Kanal	Siliconixs
1,00	B.TPMFP.4	Si2307BDS / SOT-23 / P-Kanal	Siliconixs

1,00	B.MSW.4	Miniatur-Tastschalter Serie EVQ / SMD	Panasonic, Typ EVQQ2P03W
1,00	B.MBU.2R80PS.1	80 pol. 2 reih. Federl., SMD, RM0,8	AMP C-177983-3
1,00	B.MBU.1R8PL.2	RJ45 Modular Jack, 8 pol., liegend, SMD	Tyco, Typ: C-6339160-1
1,00	B.MBU.1R5PL.1	USB-Mini-Einbaukupplung, liegend, SMD	Lumberg, Typ: 2486-01
1,00	B.MBU.1R4PL.5	USB-Einbaukupplung, liegend, SMD	FCI, Typ: 87583-2010BLF
1,00	B.MST.1R12PL.1	SD-CARD Steckverbinder	KINGFONT (multicomp)
3,00	B.MST.2R10PS.10	Stiftl.,10pol.,2reih.,steh./RM2,54, SMD	Samtec, Typ: TSM-105-01-L-DV-LC
1,00	B.MST.2R26PS.4	Stiftl.,26pol.,2reih.,steh./RM2,54, SMD	Samtec, Typ: TSM-113-01-L-DV-LC
1,00	B.MST.2R34PS.4	Stiftl.,34pol.,2reih.,steh./RM2,54, SMD	Samtec, Typ: TSM-117-01-L-DV-LC
1,00	B.MBU.1R4PK.1	KRM4, Schraubklemme, 4pol. / RM: 5	various
4,00	B.MSCHR.15	Distanzbolzen M2.5 / L=5mm sechskant	various
4,00	B.MSCHR.16	Unterlegscheibe M2.5	various
4,00	B.MSCHR.18	Schraube M2.5*4 / Zylinderkopf	various
4,00	B.MSCHR.17	Mutter M2.5	various
1,00	B.MLP.79	Leiterpl. PCOM-STARTINTF2 / 80x100 / 4L	